



Reusable push-in fasteners for metal, wood, plastic, or any thin-gauge materials. Made of nylon, they resist vibration, abrasion, corrosion, and may be used for electrical insulating.



Part No.	Hole Size (In)	Hole Size (mm)	Chassis Thickness (In)	Chassis Thickness (mm)	D (In)	D (mm)	H (In)	H (mm)	C (In)	C (mm)	L (In)	L (mm)
BB-0	.062 -.065	1.57-1.65	.010 -.031	0.25-0.79	0.100	2.54	0.020	0.51	0.068	1.73	0.125	3.18
BB-27	.062 -.065	1.57-1.65	.010 -.031	0.25-0.79	0.100	2.54	0.020	0.51	0.068	1.73	0.187	4.75
BB-22	.085 -.090	2.16-2.29	.032 -.107	0.81-2.72	0.125	3.18	0.030	0.76	0.107	2.72	0.187	4.75
BB-15	.118 -.122	3.00-3.10	.062 -.125	1.57-3.18	0.280	7.11	0.060	1.52	0.150	3.81	0.390	9.91
BB-20	.120 -.135	3.05-3.43	.062 -.125	1.57-3.18	0.270	6.86	0.040	1.02	0.140	3.56	0.330	8.38
BB-13	.130 -.132	3.30-3.35	.125 -.140	3.18-3.56	0.276	7.01	0.070	1.78	0.162	4.11	0.318	8.08
BB-1	.131 -.135	3.33-3.43	.062 -.125	1.57-3.18	0.280	7.11	0.070	1.78	0.160	4.06	0.390	9.91
BB-14	.145 -.150	3.68-3.81	.290 -.300	7.37-7.62	0.280	7.11	0.070	1.78	0.196	4.98	0.530	13.46
BB-3	.151 -.161	3.84-4.09	.062 -.125	1.57-3.18	0.280	7.11	0.040	1.02	0.196	4.98	0.390	9.91
BB-4	.151 -.161	3.84-4.09	.062 -.145	1.57-3.68	0.280	7.11	0.080	2.03	0.180	4.57	0.400	10.16
BB-18	.160 -.165	4.06-4.19	.032 -.125	0.81-3.18	0.280	7.11	0.080	2.03	0.186	4.72	0.400	10.16
BB-5	.182 -.192	4.62-4.88	.062 -.125	1.57-3.18	0.370	9.40	0.060	1.52	0.225	5.72	0.420	10.67
BB-11	.182 -.192	4.62-4.88	.165 -.185	4.19-4.70	0.380	9.65	0.060	1.52	0.206	5.23	0.518	13.16
BB-6	.182 -.192	4.62-4.88	.310 -.330	7.87-8.38	0.370	9.40	0.060	1.52	0.225	5.72	0.550	13.97
BB-28	.192 -.212	4.88-5.38	.062 -.125	1.57-3.18	0.375	9.53	0.060	1.52	0.235	5.97	0.450	11.43
BB-12	.195 -.200	4.95-5.08	.035 -.065	0.89-1.65	0.370	9.40	0.060	1.52	0.225	5.72	0.350	8.89
BB-7W	.213 -.223	5.41-5.66	.062 -.187	1.57-4.75	0.625	15.88	0.100	2.54	0.248	6.30	0.492	12.50
BB-7L	.213 -.223	5.41-5.66	.125 -.187	3.18-4.75	0.500	12.70	0.080	2.03	0.240	6.10	0.540	13.72
BB-7	.213 -.223	5.41-5.66	.125 -.187	3.18-4.75	0.370	9.40	0.060	1.52	0.240	6.10	0.540	13.72

Countless Possibilities, Millions Of Solutions
(416) 242-6811

BB-8	.213 -.223	5.41-5.66	.062 -.125	1.57-3.18	0.370	9.40	0.060	1.52	0.225	5.72	0.450	11.43
BB-26	.240 -.260	6.10-6.60	.095 -.218	2.41-5.54	0.750	19.05	0.055	1.40	0.281	7.14	0.632	16.05
BB-9	.250 -.260	6.35-6.60	.125 -.187	3.18-4.75	0.484	12.29	0.060	1.52	0.290	7.37	0.575	14.61
BB-21	.250 -.260	6.35-6.60	.125 -.250	3.18-6.35	0.500	12.70	0.050	1.27	0.280	7.11	0.630	16.00
BB-16	.250 -.260	6.35-6.60	.360 -.380	9.14-9.65	0.610	15.49	0.065	1.65	0.290	7.37	0.810	20.57
BB-24	.250 -.260	6.35-6.60	.500 -.750	12.70-19.05	0.610	15.49	0.068	1.73	0.287	7.29	1.135	28.83
BB-17V	.310 -.325	7.87-8.26	.062 -.215	1.57-5.46	0.540	13.72	0.095	2.41	0.360	9.14	0.630	16.00
BB-17	.320 -.335	8.13-8.51	.062 -.340	1.57-8.64	0.683	17.35	0.070	1.78	0.375	9.53	0.900	22.86
BB-29	.330 -.340	8.38-8.64	.125 -.350	3.18-8.89	0.475	12.07	0.070	1.78	0.370	9.40	0.895	22.73
BB-19	.330 -.340	8.38-8.64	.125 -.350	3.18-8.89	0.685	17.40	0.070	1.78	0.375	9.53	0.895	22.73
BB-23	.335 -.345	8.51-8.76	.062 -.140	1.57-3.56	0.866	22.00	0.050	1.27	0.370	9.40	0.458	11.63

Minimum order 1000.

Other sizes available: Minimum order 50,000.

Countless Possibilities, Millions Of Solutions
(416) 242-6811

62 Densley Avenue, Toronto, Ontario Canada M6M 5E1

cordscanada.com